

*Pairing with Pairing button on SD1000.

Master Device	LED Status	Slave Device	LED Status
1 Push the Reset button for 3 sec.	Mode Led On		
		2 Push the Reset button for 3 sec on Slave#1.	Mode Led On
		3 Push the Pairing button for 3 sec on Slave#1.	Mode Led Blinking (3 times per 1sec)
4 Push the Pairing button for 3 sec.	Mode Led Blinking (3 times per 1sec)		
5. Again push the Pairing button for 3 sec	Mode Led Blinking (1 time per 1sec)		
Connect with Slave#1	Connect Led Blinking	Connect with Master	Connect Led Blinking
6 Push the Pairing button for 3 sec.	Mode Led Blinking (1 time per 1sec)		
(Into the Multiple connection mode)	Mode Led On Connect Led Blinking		Connect Led Blinking
		7 Push the Reset button for 3 sec on Slave#2.	Mode Led On
		8 Push the Pairing button for 3 sec on Slave#2.	Mode Led Blinking (3 times per 1sec)
9 Push the Pairing button for 3 sec	Connect Led Blinking		
Connect with Slave#2	Mode Led On Connect Led Blinking	Connect with Master	Connect Led Blinking
		10 Push the Reset button for 3 sec on Slave#3.	Mode Led On
		11 Push the Pairing button for 3 sec on Slave#3.	Mode Led Blinking (3 times per 1sec)
12 Push the Pairing button for 3 sec	Mode Led Blinking (1 time per 1sec)		
Connect with Slave#3	Mode Led On Connect Led Blinking	Connect with Master	Connect Led Blinking
		13 Push the Reset button for 3 sec on Slave#4.	Mode Led On
		14 Push the Pairing button for 3 sec on	Mode Led Blinking (3 times per 1sec)

		Slave#4.	
15 Push the Pairing button for 3 sec	Mode Led Blinking (1 time per 1sec)		
Connect with Slave#4	Mode Led On Connect Led Blinking	Connect with Master	Connect Led Blinking